

# AL400ULM Multi-Output Power Supply/Charger

#### **Overview**

AL400ULM

AL400ULM multi-output access control power supply/charger is specifically designed for use with access control systems and accessories. This unit converts a 115VAC / 60Hz input into five (5) individually protected Class 2 Rated will route power to a va-Locks, Electric Strikes, e in both Fail-Safe and through normally open e polarity reversal from ry output relay enables rigger auxiliary devices.

riety of Magnet	nited 12VDC or 24VDC outputs. Each output will route powe access control hardware devices including Mag Locks, Electric c Door Holders, etc. These outputs will operate in both Fail- are modes. Controlled trigger input is achieved through norma
(N.O.)	r normally closed (N.C.) supervised input or the polarity rever ? (Fire Alarm Control Panel). A form "C" dry output relay
HVAC	hutdown, Elevator Recall or it may be used to trigger auxiliary
	<u>Specifications</u>
	Supervision:
mp.	• AC fail supervision (form "C" contacts).
0V.	• Low battery supervision (form "C" contacts).
Control Syster	trigger • Battery presence supervision (form "C" contact

form "C" contacts). • Power fail supervision relay (form "C" contacts).

#### Visual Indicators:

- AC input and DC output LED indicators (power supply board).
- Red LEDs indicate condition of power outputs (multi-output board).
- Power & input trigger LEDs (multi-output board).

#### Electrical:

- Operating temperature: 0° C to 49° C ambient.
- BTU/Hr.:
  - 12VDC: 24.57 BTU/Hr.
  - 24VDC: 36.85 BTU/Hr.
- System AC input VA requirement: 402.5VA.

#### Mechanical:

- Enclosure Dimensions (H x W x D approx.): 13.5" x 13" x 3.25" (342.9mm x 330.2mm x 82.55mm)
- Accommodates up to two (2) 12VDC/7AH batteries.
- Product weight (approx.): 7.6 lbs. (3.45 kg).
- Shipping weight (approx.): 8.6 lbs. (3.9 kg).

• Maximum charge current 0.7 amp.

## Agency Approvals



CSFM - California State Fire Marshal Approved.



MEA MEA - NYC Department of Buildings Approved.

## Input:

- Input 115VAC / 60Hz, 3.5 an
- Input fuse rated @ 5 amp/250
- Fire Alarm Panel or Access C inputs. N.O. or N.C. supervised trigger input and polarity reversal trigger input.

## Output:

- 12VDC or 24VDC selectable outputs.
- 12VDC @ 4 amp or 24VDC @ 3 amp supply current.
- Burglar Alarm Applications: 12VDC = 10VDC-13.2VDC;24VDC = 20VDC - 26.4VDC.
- Five (5) PTC protected Class 2 Rated power limited outputs, rated @ 2 amp.
- Output relay energizes when unit is triggered (form "C" contact rated 1 amp @ 28VDC).
- Filtered and electronically regulated output.
- Short circuit and thermal overload protection.

## **Battery Backup:**

- · Built-in charger for sealed lead acid or gel type batteries.
- Automatic switch over to stand-by battery when AC fails.



UL Listed for Access Control Systems Units (UL 294). UL Listed Standard for Power Supplies for Use with Burglar-Alarm System Units (UL 603). UL Listed Hospital Signaling and Nurse Call Equipment (UL 1069).

UL Listed Standard for Safety for Fire

Protective Signaling Systems (UL 1481).

