

# LPS3 Linear Power Supply/Charger

Rev. DSLPS3\_10312012

### **Overview**



LPS3 linear power supply/charger converts a low voltage AC input into a 12VDC/24VDC output. These units are specifically designed to provide the power needed by the most demanding security and access control applications.

# Input:

• 16VAC or 28VAC.

### Output:

- 12VDC/24VDC selectable output.
- 2.5 amp continuous supply current.
- Filtered and electronically regulated output.
- Short circuit and thermal overload protection.

### **Battery:**

- Built-in charger for sealed lead acid or gel type batteries.
- Maximum charge current 500mA.
- Automatic switch over to stand-by battery.
- Fused battery protection (circuit breaker available).

# **Specifications**

### Visual Indicators:

• AC/DC power LED indicator.

### Features:

- Includes battery leads.
- Operating temperature:  $-20^{\circ}$  C to  $49^{\circ}$  C ambient.
- BTU/Hr.:
  - 12VDC: 11 BTU/Hr.
  - 24VDC: 23 BTU/Hr.

### Mechanical:

- Product weight (approx.): 1.75 lbs. (0.79 kg.)
- Shipping weight (approx.): 1.8 lbs. (0.82 kg.)

## **Board Dimensions** (L x W x H) (approximate):

7" (177.8mm) x 4" (101.6mm) x 2" (50.8mm)

